

Tel.: +86 20 39388220
Fax: +86 20 31072811

Web: <http://www.rhaudio.com/>
Email: info@rh-audio.net

10 Zone Speaker Selector RH2813D



The RH2813D is a [10 channel speaker selector](#) having 2 amplifier inputs and 10 individual relay switches, allows the user to distribute an amplified speaker signal up to 10 listening zones. The two amplifier inputs contain A channel for BGM amplifier and B channel for EMC/paging amplifier, in this way the other zone's music system will not be interrupted when some zone is selected for paging. Paging signal from the remote microphone console enjoys auto-muting facilitates announcements overriding the BGM signal with a quick return to regular operation at any time once the paging stops.

The 25-pin alarm input bus is ready to receive the EMC. signal from its counterpart 10 [high power speaker selector](#) RH2810P, and this input has top priority over paging and BGM signal to support system to output a siren signal or a user-recorded voice alarm or siren once any emergency occurs in the venue.

- ※ [RH AUDIO](#), the best remote control speaker selector from China
- ※ Power handling: maximum 2 kW total capacity, maximum 200W per zone.
- ※ Supports 10 zones for background music, paging, and alarm broadcasting.
- ※ 2 groups of 5 zones and 70V/100V audio signal outputs.
- ※ Two amplifier inputs A and B.
- ※ LED signal level meter.
- ※ 10-position zone selector switch with pushbutton on the front panel.

Model	RH2813D
A Group Input	70V/100V, audio signal CH1~ CH5
B Group Input	70V/100V audio signal 'CH6~ CH10'
Power Handling	total capacity A, B 2000kW, per channel 200W
Power Requirements	AC220V±10%,50/60Hz
Power Consumption	10 ~ 15W
Dimension	89(H)×483(W)×366(D)mm
Net Weight	5.0 Kg



Guangzhou Xinghongde Electronics Technology Co.,Ltd.